D15 Connector at rotary viewer:

Connector pin	Description computer side and addressing		Description rotary viewer side	Direction looking from computer side.	Wire color and function language selection side
1	Bussy	Base+1 bit 7	Loopthrough to D25 con.	Input	Yellow, muxed output
2			Ground		Grey, ground
3			+12 Volt.		Pink, +12 Volts
4			+5 Volt.		Red, +5 Volts
5	D5	Base+0 bit 5	Loopthrough to D25 con.	Output	Brown, selection bit B
6	D6	Base+0 bit 6	Loopthrough to D25 con.	Output	Green, selection bit C
7	D7	Base+0 bit 7	Loopthrough to D25 con.	Output	Bleu, Not connected
8	Error	Base+1 bit 3	Loopthrough to D25 con.	Input	Not used. Not connected
9	D4	Base+0 bit 4	Loopthrough to D25 con.	Output	White, selection bit A
10					Not used
11					Not used
12					Not used
13					Not used
14					Not used
15					Not used



